Incremental encoders



Standard stainless steel, optical

Sendix 5006 / 5026 (shaft / hollow shaft)

Push-pull / RS422



The incremental Sendix encoders 5006 / 5026 in stainless steel offers optimum material resistance and thus virtually unlimited durability.

The high-grade seals, the IP66/IP67 level of protection as well as the wide temperature range additionally ensure impermeability and ruggedness.



















Safety-Lock¹

High rotational

Temperature range

High protection level

tion H

gh shaft load Shock / vibra capacity resistant

ation Magnetic nt proof

Short-circ proof

protection

Optical sens

Durable and sealed

- · Protection rating IP66/IP67.
- · Rugged stainless steel housing.
- Wide temperature range -40 ... +85°C.
- Sturdy bearing construction in Safety Lock™ Design for resistance against vibration and installation errors.

Flexible in use

- · Compatible with all common US and european standards.
- Power supply 5 ... 30 V DC, various interface options, max. 5000 pulses per revolution.
- Compact dimensions: outer diameter 50 mm, installation depth max. 47 mm.

Order code Shaft version

8.5006 . XXXX 4 . XXXX

a Flange

C = square flange

□ 63.5 mm [2.5"]

b Shaft (ø x L), with flat 1 = ø 6 x 10 mm [0.24 x 0.39"]

 $3 = \emptyset 10 \times 20 \text{ mm} [0.39 \times 0.79"]$ $8 = \emptyset 3/8" \times 7/8"$ • Output circuit / power supply

2 = push-pull (7272 compatible with inverted signal) / 5 ... 30 V DC

5 = push-pull (with inverted signal) / 10 ... 30 V DC

4 = RS422 (with inverted signal) / 5 V DC

d Type of connection

4 = radial M12 connector, 8-pin

Pulse rate

1, 5, 10, 12, 36, 100, 200, 250, 256, 360, 400, 500, 512, 600, 800, 1000, 1024, 1200, 2000, 2048, 2500, 3600, 4096, 5000 (e.g. 100 pulses => 0100)

Optional on request

- other pulse rates
- Ex 2/22
- seawater resistant (stainless steel V4A)

Stainless steel V4A as standard types (deliverable as from 1 unit)



8.5006.73X4.XXXX-V4A

Order code <u>Hollow</u> shaft

| 8.5026 | . | X | X | X | 2 | . | | X



a Flange

1 = with spring element, long

C = with stator coupling, ø 63 mm

b Through hollow shaft

2 = Ø 1/4"

 $4 = \emptyset 3/8"$

3 = Ø 10 mm [0.39"]

5 = Ø 12 mm [0.47"]

 $6 = \emptyset 1/2$ "

8 = Ø 15 mm [0.59"]

• Output circuit / power supply

2 = push-pull (7272 compatible, with inverted signal) / 5 ... 30 V DC

5 = push-pull (with inverted signal) / 10 ... 30 V DC

4 = RS422 (with inverted signal) / 5 V DC

Type of connection

2 = radial M12 connector, 8-pin

Pulse rate

1, 5, 10, 12, 36, 100, 200, 250, 256, 360, 400, 500, 512, 600, 800, 1000, 1024, 1200, 2000, 2048, 2500, 3600, 4096, 5000 (e.g. 100 pulses => 0100)

Optional on request

- other pulse rates
- Ex 2/22
- seawater resistant (stainless steel V4A)

Stainless steel V4A as standard types (deliverable as from 1 unit) 8.5026.18X2.XXXX-V4A





8.0000.5136.0000.V4A

Incremental encoders

Standard stainless steel, optical

Sendix 5006 / 5026 (shaft / hollow shaft)

M12 female connector with coupling nut, 8-pin, A-coded, straight, stainless steel

Push-pull / RS422

Mounting accessory for hollow shaft encoders Dimensions in mm [inch]		Order no.
Isolation / adapter inserts for hollow shaft encoders	D1	Isolation insert
Thermal and electrical isolation of the encoders (Temperature range -40 +115°C [-40°F +239°F]) Isolation inserts prevent currents from passing through the encoder bearings. These currents can occur when using inverter controlled three-phase or AC vector motors and considerably shorten the service life of the encoder bearings. In addition the encoder is thermally isolated as the plastic does not transfer the heat to the encoder. Tip: By using these adapter inserts you can achieve six different hollow shaft diameters, all on the basis of the encoder 8.5026.X8X2.XXXX.	6 mm [0.24"] 8 mm [0.32"] 10 mm [0.39"] 12 mm [0.47"] 1/4" 3/8" 1/2"	8.0010.4021.0000 8.0010.4020.0000 8.0010.4023.0000 8.0010.4025.0000 8.0010.4022.0000 8.0010.4024.0000 8.0010.4026.0000
Connection technology		Order no.

Further accessories can be found in the accessories section or in the accessories area of our website at: kuebler.com/accessories. Additional connectors can be found in the connection technology section or in the connection technology area of our website at: kuebler.com/connection_technology.

Technical data

Connector, self-assembly

Electrical characteristics			
Output circuit	RS422 (TTL compatible))	Push-pull	Push-pull (7272 compatible)
Power supply	5 V DC (±5 %)	10 30 V DC	5 30 V DC
Current consumption with inverted signal (no load)	typ. 40 mA max. 90 mA	typ. 50 mA max.100 mA	typ. 50 mA max.100 mA
Permissible load / channel	max. +/- 20 mA	max. +/- 20 mA	max. +/- 20 mA
Pulse frequency	max. 300 kHz	max. 300 kHz	max. 300 kHz
Signal level HI	GH min. 2.5 V W max. 0.5 V	min +V - 1.0 V max. 0.5 V	min. +V - 2.0 V max. 0.5 V
Rising edge time t _r	max. 200 ns	max. 1 μs	max. 1 μs
Falling edge time t _f	max. 200 ns	max. 1 µs	max. 1 µs
Short circuit proof outputs 1)	yes ²⁾	yes	yes
Reverse polarity protection of the power supply	no	yes	no
UL approval	file no. E224618		
CE compliant acc. to	EMC guideline 2014/30/EU RoHS guideline 2011/65/EU		

Mechanical characteristics				
Maximum speed ³⁾ 6000 min ⁻¹		Working temperature	-40°C +85°C [-40°F +185°F]	
Mass moment of inertia	approx. 1.8 x 10 ⁻⁶ kgm ²	Material housing, flange, shaft	stainless steel, 1.4305 (V2A)	
Starting torque – at 20°C [68°F]	< 0.05 Nm	connector	stainless steel	
Weight	approx. 0.4 kg [14.11 oz]	Shock resistance acc. to EN 60068-2-27	2500 m/s ² , 6 ms	
	adial 80 N axial 40 N IP66 / IP67	Vibration resistance acc. to EN 60068-2-6	100 m/s², 10 2000 Hz	

If power supply correctly applied.
 Only one channel allowed to be shorted-out:
 at +V = 5 V DC, short-circuit to channel, 0 V, or +V is permitted.
 at +V = 5 ... 30 V DC, short-circuit to channel or 0 V is permitted.



Incremental encoders

Standard stainless steel, optical

Sendix 5006 / 5026 (shaft / hollow shaft)

Push-pull / RS422

Terminal assignment

Output circuit	Type of connection	M12 conne	ector, 8-	pin							
2.4.5	5006: 4	Signal:	0 V	+V	Α	Ā	В	B	0	ō	Ť
2, 4, 5	5026: 2	Pin:	1	2	3	4	5	6	7	8	PH 1)

+V: Encoder power supply +V DC

0 V:

Encoder power supply ground GND (0 V) Incremental output channel A Α, \\
\bar{A}: B, \overline{B} : Incremental output channel B

0, $\overline{0}$: Reference signal

PH ±: Plug connector housing (shield)

Top view of mating side, male contact base




M12 connector, 8-pin


Dimensions shaft version

Dimensions in mm [inch]

Synchro flange, ø 58 [2.28] Flange type A

1 3 x M4, 6 [0.24] deep






D	Fit	L
6 [0.24]	h7	10 [0.39]
10 [0.39]	f7	20 [0.79]
3/8"	h8	7/8"

Clamping flange, ø 58 [2.28] Flange type 7

1 3 x M3, 5.5 [0.22] deep


D	Fit	L
6 [0.24]	h7	10 [0.39]
10 [0.39]	f7	20 [0.79]
3/8"	h8	7/8"



72 2,83


⊕

37[1,46]




Square flange, ☐ 63.5 [2.5]
Flange type C

D	Fit	L
6 [0.24]	h7	10 [0.39]
10 [0.39]	f7	20 [0.79]
3/8"	h8	7/8"



10[0,39]

Ø36[1,42] Ø58 2,28



¹⁾ PH = shield is attached to connector housing.



Incremental encoders

Standard stainless steel, optical

Sendix 5006 / 5026 (shaft / hollow shaft)

Push-pull / RS422


Dimensions hollow shaft version


Dimensions in mm [inch]

Flange with spring element, long Flange type 1

- 1 3 x M3, 6 [0.24] deep
- 2 Slot spring element, recommendation: cylindrical pin DIN 7, ø 4 [0.16]
- 3 Recommended torque for the clamping ring 0.6 Nm

D	Fit
10 [0.39]	H7
12 [0.47]	H7
15 [0.99]	H7
1/4"	H7
3/8"	H7
1/2"	H7





Flange with stator coupling, ø 63 [2.48] Flange type C

1 Recommended torque for the clamping ring 0.6 Nm

D	Fit
10 [0.39]	H7
12 [0.47]	H7
15 [0.99]	H7
1/4"	H7
3/8"	H7
1/2"	H7

